

infiniium DCA Agilent 86100A Wide-Bandwidth Oscilloscope

Technical Specifications



- Modular platform for testing waveforms up to 40 Gb/s
- Easier to use through a simplified user interface
- Faster measurement throughput
- Improved measurement accuracy and repeatability
- Compatible with Agilent 83480A-series and 54750-series modules



Three Instruments in One

For basic oscilloscope operation there is easy front panel access with that familiar analog-look and feel. A Windows®-based system let's you easily navigate through the user-interface. The 86100A Infiniium DCA can be viewed as three high-performance instruments in one. It's a general-purpose repetitive sampling oscilloscope. It's a digital communications analyzer. It's a time domain reflectometer. Just select the instrument mode and start making measurements.

Digital Communications Analysis

Accurate eye-diagram analysis is essential for characterizing the quality of transmitters used from 100 Mb/s to 40 Gb/s. The 86100A was designed specifically for the complex task of analyzing digital communications waveforms. Compliance mask and parametric testing no longer require a complicated sequence of setups and configurations. If you can press a button, you can perform a complete compliance test. The important measurements you need are right at your fingertips, including:

- industry standard mask testing with built-in margin analysis,
- extinction ratio measurements with improved accuracy and repeatability, and
- eye measurements: crossing %, eye height and width, '1' and '0' levels, jitter, rise or fall times and more.

The key to accurate measurements of lightwave communications waveforms is the optical receiver. The 86100A has a broad range of precision receivers integrated within the instrument.

- Built-in photodiodes, with flat frequency responses, yield the highest waveform fidelity. This provides high accuracy for extinction ratio measurements.
- Standards-based transmitter compliance measurements require filtered responses. The 86100A has a broad range of filter combinations. Filters can be automatically and repeatably switched in or out of the measurement channel remotely over GPIB or with a front panel button. The frequency response of the entire measurement path is calibrated, and will maintain its performance over long-term usage.
- The integrated optical receiver provides a calibrated optical channel. With the accurate optical power meter built into the module, optical signals are accurately measured and displayed in optical power units. Switches or couplers are not required for an average power measurement. Signal routing is simplified and signal strength is maintained.



The integrated optical channel can be used as a fully calibrated SONET/SDH/Gigabit Ethernet or Fibre Channel reference receiver or as a wide-bandwidth receiver.

Eye Diagram Mask Testing

The 86100A provides efficient, high-throughput waveform compliance testing with a suite of standards based eye-diagram masks. The test process has been streamlined into a minimum number of keystrokes for testing at industry standard data rates.

Standard Masks

- 1X Gigabit Ethernet
- 2X Gigabit Ethernet
- 10X Gigabit Ethernet
- Fibre Channel 0133
- Fibre Channel 0266
- Fibre Channel 1063
- Fibre Channel 2125
- STM0/OC1
- STM1/OC3
- STM4/OC12
- STM16/OC48
- STM64/OC192
- STS1 EYE
- STS3 EYE

Other eye-diagram masks are easily created through scaling those listed above. In addition, mask editing allows for new masks either by editing existing masks, or creating new masks from scratch. The mask data can be entered or modified on an external PC using a text editor such as Notepad, then can be transferred to the instrument's hard drive using LAN or the A: drive. Once in the instrument, the mask can be used for mask test.

Perform these mask conformance tests with convenient user-definable measurement conditions, such as mask margins for guardband testing, number of waveforms tested, and stop/limit actions.

Measurement Speed

Measurement speed has been increased with both fast hardware and a user-friendly instrument. In the lab, don't waste time trying to figure out how to make a

Windows is a U.S. registered trademark of Microsoft Corporation.

measurement. With the simple-to-use 86100A, you don't have to relearn how to make a measurement each time you use it. In manufacturing, it is a battle to continually reduce the cost per test. Solution: Fast PC-based processors, resulting in high measurement throughput and reduced test time.

Measure

Standard Measurements/Features

The following measurements are available from the tool bar, as well as the pull down menus. Measurements available are dependent on the DCA operating mode.

Oscilloscope Mode

Time

Rise Time, Fall Time, Jitter RMS, Jitter p-p, Period, Frequency, + Pulse Width, - Pulse Width, Duty Cycle, Delta Time, [T_{max}, T_{min}, T_{edge}—remote commands only]

Amplitude

Overshoot, Average Power, V amptd, V p-p, V rms, V top, V base, V max, V min, V avg

Eye/Mask Mode

NRZ Eye Measurements

Extinction Ratio, Jitter RMS, Jitter p-p, Average Power, Crossing Percentage, Rise Time, Fall Time, One Level, Zero Level, Eye Height, Eye Width, Signal to Noise (Q-Factor), Duty Cycle Distortion, Bit Rate, Eye Amplitude

RZ Eye Measurements

Extinction Ratio, Jitter RMS, Jitter p-p, Average Power, Rise Time, Fall Time, One Level, Zero Level, Eye Height, Eye Amplitude, Opening Factor, Eye Width, Pulse Width, Signal to Noise (Q-Factor), Duty Cycle, Bit Rate, Contrast Ratio

Mask Test

Open Mask, Start Mask Test, Exit Mask Test, Filter, Mask Test Margins, Mask Test Scaling

TDR/TDT Mode

Quick TDR, TDR/TDT Setup, Normalize, Response, Rise Time, Fall Time, Δ Time

Standard Functions

Standard functions are available through pull down menus and soft keys, and some functions are also accessible through the front panel knobs

Markers

Two vertical and two horizontal, user selectable

TDR Markers

Horizontal - seconds or meter Vertical - volts, ohms or Percent Reflection Propagation - Dielectric Constant or Velocity

Limit Tests

Acquisition Limits Limit Test Run Until Conditions - Off, # of Waveforms, # of Samples

Report Action on Completion - Save waveform to memory or disk, Save screen image to disk

Measurement Limit Test

Specify Number of Failures to Stop Limit Test

When to Fail Selected Measurement - Inside Limits, Outside Limits, Always Fail, Never Fail

Report Action on Failure - Save waveform to memory or disk, Save screen image to disk, Save summary to disk

Mask Limit Test

Specify Number of Failed Mask Test Samples

Report Action on Failure - Save waveform to memory or disk, Save screen image to disk, Save summary to disk

Configure Measurements

Thresholds

 $10\%,\,50\%,\,90\%$ or $20\%,\,50\%,\,80\%$ or Custom

Eye Boundaries 1 and 2

Format Units for

Duty Cycle Distortion - Time or Percentage Extinction Ratio - Ratio, Decibel or Percentage Eye Height - Amplitude or Decibel (dB) Eye Width - Time or Ratio Average Power - Watts or Decibels (dB)

Top Base Definition

Standard or Custom

Δ Time Definition

First Edge Number, Edge Direction, Threshold Second Edge Number, Edge Direction, Threshold

Quick Measure Configuration

4 User Selectable Measurements for Each Mode

Eye/Mask Mode Default Settings

Extinction Ratio, Jitter RMS, Average Power, Crossing Percentage

Oscilloscope Mode Default Settings

Rise Time, Fall Time, Period, V amptd

Histograms

Configure Histogram State Histogram Axis Histogram Window

Window Adjustable Window via Marker Knobs

Scale 1 to 8 divisions

Axis

Math Measurements 4 User Definable Functions Operator - Magnify, Invert, Subtract, Versus, Min, Max

Source - Channel, Function, Memory, Constant, Response (TDR)

Set up and Info

Annotate Measurements Algorithm Configuration

Calibrate

All Calibrations

Vertical (Amplitude) Horizontal (Time Base) Extinction Ratio Probe Optical Channel

Front Panel Calibration Output Level User Selectable –2V to 2V

Horizontal Skew Adjustment Per Channel, User Selectable

<u>Utilities</u>

Set Time and Date Show Time and Date

Remote Interface Set GPIB Interface

Touch Screen Configuration

Calibration Display TouchSurround Buttons Interface

Upgrade Software Upgrade Mainframe Upgrade Module

Help

Content

About 86100A

Mainframe Serial Number Module Serial Number Software Revision and date Hard Disk free space



File Sharing and Storage

Use the internal 5.5 GB hard drive or 3.5 inch, 120 MB SuperDisk[™] floppy disk drive to store instrument setups, waveforms, or screen images. Images can be stored in formats easily imported into



Configurable to Meet Your Needs

The 86100A supports a wide range of plug-ins for testing both optical and electrical signals. Select plugins to get the specific bandwidth, filtering, and sensitivity you need.

Built-in Information System

The 86100A has a context-sensitive on-line manual providing immediate answers to your questions about using the instrument. Links on the measurement screen take you directly to the information you need. There is no need for a large paper manual consuming your shelf space. various programs for documentation and further analysis. LAN interface is also available for network file management and printing.

Powerful Display Modes

Use gray scale and color graded trace displays to gain insight into device behavior. Waveform densities are mapped to color or easy-to-interpret gray shades. These are infinite persistence modes where shading differentiates the number of times data in any individual screen pixel has been acquired.

Internal Triggering Through Clock Recovery

Very high-speed oscilloscopes are not capable of triggering directly on the signal under test. Typically an external timing reference is used to synchronize the oscilloscope to the test signal. In cases where a trigger signal is not available, clock recovery modules are available to derive a timing reference directly from the waveform to be measured. The Agilent 8349XA series of clock recovery modules cover the three most popular transmission media used today—electrical lines, multimode, and single-mode fiber. A built-in coupler reduces external hardware requirements. All four modules have excellent jitter performance to ensure accurate measurements. Each clock recovery module is designed to synchronize to a variety of common transmission rates.

Improved Autoscaling

Autoscaling has been significantly improved to provide quick horizontal and vertical scaling of both pulse and eye-diagram (RZ and NRZ) waveforms. tion for circulating loop or burst-data experiments. Use TTL-compatible signals to control when the instrument does and does not acquire data.

Easier Calibrations

Calibrating your instrument has been simplified by placing all the performance level indicators and calibration procedures in a single high-level location. This provides greater confidence in the measurements made and saves time in maintaining equipment.

Stimulus Response Testing Using the Agilent 86130A BitAlyzer®

Error performance analysis represents an essential part of digital transmission test. The Agilent 86100A and 86130A BitAlyzer error performance analyzer share a common interface and together create a powerful test solution.

Transitioning from the Agilent 83480A to the 86100A

The 86100A has been designed to be a virtual drop-in replacement for the Agilent 83480A digital communications analyzer and Agilent 54750A wide-bandwidth oscilloscope. All modules used in the Agilent 83480A and 54750A can also be used in the 86100A. The remote programming command set for the 86100A has been designed for direct compatibility with software written to control the 83480A and 54750A. (Due to improvements and updates in performance, a small set of remote commands may need minor modifications to control the 86100A.) Due to a significantly faster processor and improved measurement algorithms, tests run on the 86100A should require less time than

those performed with the 83480A or 54750A.

Modules for the 86100A Infiniium DCA

The 86100A has a large family of plug-in modules designed for a broad range of data rates for optical and electrical waveforms. The 86100A can hold up to 2 modules for a total of 4 measurement channels.

The Agilent 86101A module and 86103A has two measurement channels, one optical and one electrical. The electrical channel

BitAlyzer is a U.S. registered trademark of SyntheSys Research, Inc.

Time Domain Reflectometer (TDR)

TDR measurements are focused on high-speed applications where it is necessary to optimize electrical system components, such as microstrip lines, PC board traces, SMA edge launchers and coaxial cables where imperfections cause signal distortion and reflections. Signal integrity is a critical requirement in highspeed digital signal transmission.

Gated Triggering

Trigger gating port allows easy external control of data acquisi-



has two selectable bandwidth settings. The 12.4 GHz bandwidth mode provides the best oscilloscope noise performance. The 20 GHz mode allows greater fidelity for high-speed signals. The calibrated, integrated optical channel has over 2.85 GHz bandwidth for easy, precise single mode and multimode optical measurements. The 86101A and 86103A utilize switchable reference filters for transceiver compliance testing at OC-3, OC-12, OC-48, Fibre Channel 1063 Mb/s, and Gigabit Ethernet 1250 Mb/s data rates. The 86101A operates over the 750 nm to 860 nm wavelength range, and the 86103A operates over the 1000 nm to 1600 nm wavelength range.

The Agilent 86105A module has two measurement channels, one optical and one electrical. The electrical channel has two selectable bandwidth settings. The 12.4 GHz bandwidth mode provides the best oscilloscope noise performance. The 20 GHz mode allows greater fidelity for high-speed signals. The calibrated, integrated optical channel has 20 GHz bandwidth for single mode optical measurements. The 86105A utilizes switchable reference filters for transceiver compliance testing at OC-3, OC-12, OC-48 or OC-192 data rates.

The Agilent 86106B module has a 28 GHz optical channel and 40 GHz electrical channel. Both channels have a reduced bandwidth setting of 20 GHz for improved noise performance. The calibrated, integrated optical channel has a switchable reference filter for transceiver compliance testing at OC-192 (9.953 Gb/s).

The Agilent 86109A module has a 30 GHz optical measurement channel and a 40 GHz electrical channel. The electrical channel also has a reduced bandwidth setting of 18 GHz for improved noise performance. The optical channel frequency response is designed to minimize distortion of the displayed optical pulse and does not include any provision for switching a SDH/SONET filter into the channel.

The Agilent 86112A electrical module provides two electrical measurement channels with user selectable bandwidths. The 12.4 GHz bandwidth mode provides excellent oscilloscope noise performance for accurate measurement of small signals. The 20 GHz bandwidth mode provides high fidelity display and measurement of very high-speed waveforms.

The Agilent 83484A electrical module provides two electrical measurement channels with user selectable bandwidths. The 26.5 GHz bandwidth mode provides excellent oscilloscope noise performance for accurate measurement of small signals. The 50 GHz bandwidth mode provides high fidelity display and measurement of very high-speed waveforms.

The Agilent 83494A single-mode clock recovery plug-in module is an integrated solution for high-speed digital transmission test. When a separate trigger source is not available, the 83494A can derive a timing reference directly from the signal under test. The 83494A can synchronize to all SONET/SDH transmission rates through 10 Gb/s with exceptional jitter performance that ensures an accurate display of the test waveform.

The Agilent 8349xA series of clock recovery modules provide a recovered clock trigger and recovered data output, and the ability to trigger on data for slower nonstandard rates. The 83491A accepts electrical inputs, the 83492A accepts multimode fiber inputs, and the 83493A accepts single mode fiber inputs. All three clock recovery modules support standard telecom and enterprise data rates.

The Agilent 54753A single-ended TDR module has TDR step generator built into channel one. The bandwidth of the TDR/vertical channel is 18 GHz. The bandwidth of channel two is 20 GHz.

The Agilent 54754A differential TDR module has two independent vertical channels and two step generators. The bandwidth of both channels is 18 GHz. The step generators may be operated singly, simultaneously but independently, differentially, or as common-mode stimulus. The TDR results may be viewed as common mode or differentially and displayed simultaneously. Once selected, the display mode is computed automatically, freeing the user from setting up mathematical functions. Included with each of these TDR modules is a TDR demo board, programmers guide, 250Ω terminations, APC-3.5 (m), and one short, APC-3.5 (m).

Specifications

Specifications describe warranted performance over the temperature range of +10°C to + 40°C (unless otherwise noted). The specifications are applicable for the temperature after the instrument is turned on for one (1) hour. This period of continuous operation must occur while self-calibration is valid. Many performance parameters are enhanced through frequent, simple user calibrations. *Characteristics provide useful, non-warranted information about the functions and performance of the instrument. Characteristics are printed in italic typeface.*

Factory Calibration Cycle -For optimum performance, the instrument should have a complete verification of specifications once every twelve (12) months.

General Specifications

This instrument meets Agilent Technologies' environmental specifications (section 750) for class B-1 products with exception as described for temperature and condensation. Contact your local field engineer for complete details.

lz axis

Mainframe Specifications

HORIZONTAL SYSTEM (Time Base) Scale Factor Minimum Maximum Delay Minimum Maximum Time Interval Accuracy Time Interval Resolution Display Units	Full scale is ten divisions. 2 ps/div 1 s/div Time offset relative to the front panel trigger input on the instrument mainframe. \geq 24 ns (Standard), 28 ns (Option 001) 1000 screen diameters or 10 s, whichever is smaller \leq 8 ps + 0.1% of reading (dual marker measurement performed at a temperature within ±5°C of horizontal calibration temperature) 8 ps + 0.1% + 0.5 ps/°C to (5 < absolute temperature value <15°C) \leq (screen diameter)/(record length) or 62.5 fs, whichever is larger Bits or time
VERTICAL SYSTEM (Channels)	4 (simultaneous acquisition)
Number of Channels	12 bit A/D converter (up to 15 bits with averaging)
Vertical Resolution	Adjusts in a 1-2-5-10 sequence for coarse adjustment or fine adjustment resolution from the
Full Resolution Channel Scales	front panel knob
Adjustments	Scale, offset, activate filter

Mainframe Specifications (continued)

	Standard (Direct Trigger)	Option 001 (Divided Trigger)		
Trigger Modes:		· · · · · · · · · · · · · · · · · · ·		
Internal Trigger ¹	Freerun			
External Direct Trigger ²				
Limited Bandwidth ³	DC to 100 MHz			
Full Bandwidth	DC to 2.75 GHz			
External Divided Trigger		2 to 12 GHz (1 to 15 GHz)		
Jitter				
Characteristic	1.0 ps RMS + 5*10E-5 of delay setting ⁴	1.2 ps RMS for time delays less than 100 ns		
Maximum	1.5 ps RMS + 5*10E-5 of delay setting ⁴	1.7 ps RMS for time delays less than 100 ns		
Sensitivity	200 m Vpp (sinusoidal input or 200 ps minimum pulse width)	200 m Vpp sinusoidal input from 2 to 12 GHz		
Trigger Configuration				
Trigger Level Adjustment	-1 V to + 1 V	AC coupled		
Edge Select	Positive or negative			
Hysteresis ⁵	Normal or high sensitivity			
Trigger Gating:				
Gating Input Levels	Disable: 0 to 0.6 V			
(TTL compatible)	Enable: 3.5 to 5 V			
	Pulse width >500 ns, period >1 μs			
Gating Delay	Disable: 627 ns + trigger period +			
	Max time displayed			
	Enable: 100 ns			
Trigger Impedance:				
Nominal Impedance	50Ω	50Ω		
Reflection	10% for 100 ps rise time	10% for 100 ps rise time		
Connector Type	3.5 mm (male)	3.5 mm (male)		
Maximum Trigger Signal	± 2 V + 2 Vac peak (+16 dBm)			

¹ The freerun trigger mode internally generates an asynchronous trigger that allows viewing the sampled signal amplitude without an external trigger signal but provides no timing information. Freerun is useful in troubleshooting external trigger problems.

² The sampled input signal timing is recreated by using an externally supplied trigger signal that is synchronous with the sampled signal input.

³ The DC to 100 MHz mode is used to minimize the effect of high frequency signals or noise on a low frequency trigger signal.

 4 Measured at 2.5 GHz with the triggering level adjusted for optimum trigger.

⁵ High Sensitivity Hysteresis Mode improves the high frequency trigger sensitivity but is not recommended when using noisy, low frequency signals that may result in false triggers without normal hysteresis enabled.

Computer System and Storage

CPU	300 MHz Microprocessor		
Disk Drive	5.5 GByte internal hard drive and 3.5" MS-DOS [®] compatible 120 MB SuperDisk floppy disk drive.		
	Store and recall setups, waveforms, and screen images to both the hard drive and the floppy		
	drive. Storage capacity is limited only by disk space.		
File Types/Management	Setup files .SET		
	Waveform files .WFM (internal)		
	Color grade gray scale files .CGS		
Waveforms	Internal, verbose,Y values		
Images	bmp, eps , gif, pcx, ps, jpeg, tif		
Operating System	Microsoft Windows 98		
Waveform Store	4 nonvolatile waveform memories		
	Waveform memory setup (for each channel) (vertical scale, offset, horizontal scale, position)		
Printer	Configure Printer		
	Options		
	Waveform only		
	Include instrument setup info		
	Monochrome		
	Invert waveform background color		
	Add printer		
DISPLAY			
Display Area	170.9 mm x 128.2 mm (8.4 inch diagonal color active matrix LCD module incorporating amorphous		
	silicon TFTs)		
Active Display Area	171mm x 128 mm (21,888 square mm) 6.73 in x 5.04 in (33.92 square inches)		
Waveform Viewing Area	103 mm x 159 mm (4.06 in x 6.25 in)		
Entire Display Resolution	640 pixels horizontally x 480 pixels vertically		
Graticule Display Resolution	451 pixels horizontally x 256 pixels vertically		

MS-DOS is a U.S. registered trademark of Microsoft Corporation.

Mainframe Specifications (continued)

DISPLAY (continued)			
Waveform Colors	Select from 100 hues, 0–100% saturation and 0–100% luminosity		
Persistence Modes	Gray scale, color grade, variable, infinite		
Waveform Overlap	When two waveforms overlap, a third color distinguishes the overlap area		
Connect-the-dots	On/Off selectable		
Persistence	Minimum, Variable (100 ms to 40 s), Infinite		
Graticule	On/Off		
Grid Intensity	0 to 100%		
Backlight Saver	2 to 8 hrs, enable option		
Dialog Boxes	Opaque or transparent		

	-
Cal	BNC (female) and test clip, banana plug
Trigger	APC 3.5 mm, 50 Ω , ±2 V maximum
GPIB	Fully programmable, complies with IEEE 488.2
RS-232	Serial Printer, 9 pin D-sub (male)
Centronics	Parallel Printer port, 25 pin D-sub (female)
+15 V Bias	100 ma, 15 V, SMB
Mouse	PS/2
Gated Trigger Input	TTL compatible
Keyboard	IBM 5 pin (female) (for optional keyboard)
LAN	A keyboard must be used to setup LAN connectivity
Video Output	VGA, full color, 15 pin D-sub (female)

Module Specifications

	Optical Channel Electrical Channel							
	Number of Optical Channels	Wavelength	Unfiltered Bandwidth GHz	Filter Option Data Rates (select one) Mb/s	Fiber Input	Sensitivity (smallest power for mask test)	Number of Electrical Channels	Bandwidth GHz
86101A	1	750–860 nm	2.85	Option 201: OC-3/STM-1 & OC-12/STM-4 Option 202: Fibre Channel & Gigabit Ethernet	62.5/125 μm	—17 dBm	1	12.4/20
86103A	1	1000–1600 nm	2.85	Option 201: OC-3/STM-1 & OC-12/STM-4 Option 202: Fibre Channel & Gigabit Ethernet	62.5/125 μm	—20 dBm	1	12.4/20
86105A	1	1000–1600 nm	20	Option 101: 0C-3/STM-1 Option 102: 0C-12/STM-4 Option 103: 0C-48/STM-16 Option 201: 0C-12/STM-4 & 0C-48/STM-16 Option 202: 0C-48/STM-16 & 0C-192/STM-64	9/125 µm	—8 dBm	1	12.4/20
86106B	1	1000–1600 nm	28	Standard: OC-192/STM-64 Option 410: OC-192/STM-64, 10 Gigabit Ethernet & OC-192/STM-64 FEC	9/125 µm	—7 dBm	1	18/40
86109A	1	1000–1600 nm	30		9/125 µm	N/A	1	18/40
83484A	0						2	26.5/50
86112A	0	_					2	20
54753A	0		—				1 TDR/ Elec. & 1 Elec.	12/18 & 12/20
54754A	0						2 TDR/ Elec.	12/18

TDR System	Oscilloscope/TDR Performance	Normalized Characteristics
Rise Time	40 ps nominal	Adjustable from larger of 10 ps or 0.08 x time/div Maximum: 5 x time/div
TDR Step Flatness	$\leq \pm 1\%$ after 1 ns from edge $\leq \pm 5\%$, -3% 1 ns from edge	≤0.1%
Low Level High Level	0.00 V ±2 mV ±200 mV ± mV	0.00 V ±2 mV ±200 mV ± mV

Module Specifications (continued)

Multi Mode and Single Mode						
Optical/Electrical Modules	86101A	86103A	86105A			
OPTICAL CHANNEL SPECIFICATIONS	OPTICAL CHANNEL SPECIFICATIONS					
Optical Channel Unfiltered Bandwidth	2.85 GHz (3 GHz typical)		20 GHz			
Wavelength Range	750–860 nm	1000–	-1600 nm			
Calibrated Wavelengths	850 nm	1310 nm/1550 nm	1310 nm/1550 nm			
Filtered Data Rates (Mb/s)	155, 622, 1063, 1250	155, 622, 1063, 1250	155, 622, 2488, 9953			
Sensitivity (smallest avg. power for mask test)	—17 dBm	–20 dBm	8 dBm			
Transition Time (10% to 90% calculated from T	R = 0.48/BW optical)					
Filtered	<190 ps/0C-48, <750 ps/0C-1	12, <3 ns/0C-3				
Unfiltered	160 ps	s or less	24 ps			
RMS Noise						
Characteristic	1.5 μW	1 μW, opt 201	8 μW, 12.4 GHz			
		1.5 μW, opt 202	15 μW, 20 GHz			
Maximum	2.5 μW	1.5 μW, opt 201	12 μW, 12.4 GHz			
		2.5 μW, opt 202	25 μW, 20 GHz			
Scale Factor (per division)						
Minimum	5 µ	IW	20 μW			
Maximum	100	μW	500 μW			
dc Accuracy (single marker, referenced to	±6 µW ±0.4%	6 of full scale	$\pm 25 \ \mu\text{W} \pm 2\%$ of (reading- channel			
average power monitor, <50 μW/division)	±3% of (reading-channel offset)		offset), 12.4 GHz ±25 µW ±4% of			
			(reading-channel offset), 20 GHz			
dc Difference (two markers, referenced to	±0.8% c	of full scale	±2% of (reading-channel			
average power monitor, 50 µW/division)	±3% of (readi	ng-channel offset)	offset),12.4 GHz			
			±4% of (reading-channel offset),			
			20 GHz			
dc Offset (referenced two divisions						
from screen bottom)	+0.2 mW	to –0.6 mW	1 mW to –3 mW			
Average Power Monitor						
(specified operating range)	-30 dBm to -2.2 dBm -30 dBm to 0 dBm		-30 dBm to +3 dBm			
Factory Calibrated Accuracy	±5% ±100 nW ±connector uncertainty, 20°C to 30°C					
User Calibrated Accuracy	±2% ±100 nW ±power meter uncertainty, <5°C change					
Maximum Input Power						
Specified	0.4 mW (-4 dBm) peak 2 mW (+3 dBm)		2 mW (+3 dBm)			
Maximum Peak	10 mW (+10 dBm)					
Fiber Input	62.5/125 μm, user selectable connector 9/125 μm single-mode		9/125 µm single-mode			
Input Return Loss						
(HMS-10 connector fully filled fiber)	20 dB		33 dB			

ELECTRICAL CHANNEL SPECIFICATIONS

Electrical Channel Bandwidth	12.4 and 20 GHz
Transition Time	28.2 ps, 12.4 GHz
(10% to 90%, calculated from TR = 0.48/BW)	17.5 ps, 20 GHz
RMS Noise	0.25 mV, 12.4 GHz
Characteristic	0.5 mV, 20 GHz
Maximum	0.5 mv, 12.4 GHz
	1 mV, 20 GHZ
Scale Factor	
Minimum	1 mV/division
Maximum	100 mV/division
dc Accuracy (single marker, referenced to	±0.4% of full scale
average power monitor)	± 2 mV $\pm 1.5\%$ of (reading-channel offset), 12.4 GHz
	$\pm 0.4\%$ of full scale ± 2 mV $\pm 3\%$ of (reading-channel offset), 20 GHz
dc Difference (two markers, referenced to	$\pm 0.8\%$ of full scale $\pm 1.5\%$ of delta, 12.4 GHz
average power monitor, 50 µW/division)	$\pm 0.8\%$ of full scale $\pm 3\%$ of delta, 20 GHz
dc Offset (referenced two divisions	±500 mV
from screen bottom)	
Input Dynamic Range	±400 mV
(relative to channel offset)	
Maximum Input Power	16 dBm ±2 Vdc
Nominal Impedance	50 ohm
Reflections (for 30ps rise time)	5%
Electrical Input	3.5 mm

Module Specifications (continued)

High Bandwidth, Single Mode Optical/		
Electrical Modules	86106B	86109A
OPTICAL CHANNEL SPECIFICATIONS		
Optical Channel Unfiltered Bandwidth	28 GHz	30 GHz
Wavelength Range	1000–1	600 nm
Calibrated Wavelengths	<u>1310 nm ar</u>	nd 1550 nm
Filtered Data Rates (Mb/s)	9953	No internal filters
Sensitivity (smallest average power for mask test)	–7 dBm	N/A
Transition Time (10% to 90%,		
calculated from TR = 0.48/BW optical)	18 ps	16 ps
RMS Noise		
Characteristic	10 μW (Filtered)	15 μW (Unfiltered)
	18 μW (Unfiltered)	
Maximum	15 μW (Filtered)	30 μW (Unfiltered)
	30 µW (Unfiltered)	
Scale Factor		
Minimum	20 µW/division	
Maximum	500 μW/division	
dc Accuracy (single marker, referenced to	±50 μW ±4% of (reading-chan	nel offset)
average power monitor)		
dc Difference (two markers, referenced to average power	±4% of delta	
monitor, 50 μW/division)		
dc Offset (referenced two divisions from screen bottom)	+1 mW to –3 mW	
Average Power Monitor (specified operating range)	-27 dBm to +3 dBm (2 μ W to 2	2 mW)
Factory Calibrated Accuracy	±5% ±100 nW ±connector und	ertainty, 20°C to 30°C
User Calibrated Accuracy	±2% ±100 nW ±power meter i	uncertainty, <5°C change
Maximum Input Power		
Specified	2 mW (+3 dBm)	
Maximum Peak	10 mW (+10 dBm)	
Fiber Input	9/125 µm, user selectable	
Input Return Loss (HMS-10 connector fully filled fiber)	30 dB	

¹ Specified with 8 point moving average in frequency response

ELECTRICAL CHANNEL SPECIFICATIONS

Electrical Channel Bandwidth	18 and 40 GHz
Transition Time (10% to 90%,	19.5 ps, 18 GHz; 9 ps, 40 GHz
calculated from $TR = 0.35/BW$)	
RMS Noise	
Typical	0.25 mV, 18 GHz; 0.5 mV, 40 GHz
Maximum	0.5m V, 18 GHz; 1.0 mV, 40 GHz
Scale Factor	
Minimum	1 mV/division
Maximum	100 mV/division
dc Accuracy (single marker, referenced to average	$\pm 0.4\%$ of full scale ± 2 mV $\pm 1.5\%$ of (reading-channel offset), 18 GHz
power monitor)	$\pm 0.4\%$ of full scale ± 2 mV $\pm 3\%$ of (reading-channel offset), 40 GHz
dc Difference (two markers, referenced to average	$\pm 0.8\%$ of full scale $\pm 1.5\%$ of delta, 18 GHz
power monitor, 50 μW/division)	$\pm 0.8\%$ of full scale $\pm 3\%$ of delta, 40 GHz
dc Offset (referenced two divisions from screen bottom)	±500 mV
Input Dynamic Range (relative to channel offset)	±400 mV
Maximum Input Power	16 dBm ±2 Vdc
Nominal Impedance	50 ohm
Reflections (for 20 ps rise time)	5%
Electrical Input	2.4 mm

Module Specifications (continued)

Dual Electrical Channel Modules	86112A	83484A	54753A	54754A
Electrical Channel Bandwidth	12.4 and 20 GHz	26.5 and 50 GHz	12.4 and 20 GHz	12.4 and 18 GHz
Transition Time (10% to 90%, calculated from TR = 0.35/BW)	28.2 ps, 12.4 GHz; 17.5 ps, 20 GHz	13.2 ps, 26.5 GHz; 7 ps, 50 GHz	28.2 ps, 12.4 GHz; 17.5 ps, 20 GHz	28.2 ps, 12.4 GHz; 19.4 ps, 18 GHz
RMS Noise				
Characteristic	0.25 mV, 12.4 GHz; 0.5 mV, 20 GHz	0.46 mV, 26.5 GHz; 0.92 mV, 50 GHz	0.25 mV, 12.4 GHz; 0.5 mV, 20 GHz	0.25 mV, 12.4 GHz; 0.5 mV, 18 GHz
Maximum	0.5 mv, 12.4 GHz; 1 mV, 20 GHz	0.75 mV, 26.5 GHz 1.5 mV, 50 GHz	0.5 mv, 12.4 GHz; 1 mV, 20 GHz	0.5 mv, 12.4 GHz; 1 mV, 18 GHz
Scale Factor				•
Minimum	1 mV/division			
Maximum	100 mV/division			
dc Accuracy (single marker, referenced to average power monitor)	±0.4% of full scale ±2mV ±1.5% of (reading- channel offset), 12.4 GHz ±0.4% of full scale ±2 mV ±3% of (reading- channel offset), 20 GHz	±0.4% of full scale ±2 mV ±1.2% of (reading-channel offset), 26.5 GHz ±0.4% of full scale ±2 mV ±2% of (reading- channel offset), 50 GHz	±0.4% of full scale or n (whichever is greater) ±2 mV ±1.2% of (readi	narker reading ng-channel offset)
dc Difference (two markers, referenced to average power monitor, 50 µW/division)	$\begin{array}{l} \pm 0.8\% \text{ of full scale} \\ \pm 1.5\% \text{ of delta, } 12.4 \text{ GHz} \\ \pm 0.8\% \text{ of full scale} \\ \pm 3\% \text{ of delta, } 20 \text{ GHz} \end{array}$	$\pm 0.8\%$ of full scale $\pm 1.2\%$ of delta, 26.5 GHz $\pm 0.8\%$ of full scale $\pm 2\%$ of delta, 50 GHz		
dc Offset (referenced two divisions from screen bottom)	±500 mV	±500 mV	±500 mV	
Input Dynamic Range (relative to channel offset)	±400 mV	±400 mV	±400 mV	
Maximum Input Power	16 dBm ±2 Vdc	16 dBm ±2 Vdc	16 dBm ±2 Vdc	
Nominal Impedance	50 ohm	50 ohm	50 ohm	
Reflections (for 30 ps rise time)	5%	5%	5%	
Electrical Input	3.5 mm	2.4 mm	3.5 mm	

Clock Recovery Single Mode,				
Multimode and Electrical Modules	83491A	83492A	83493A	83494A
Channel Type	Electrical	Multimode Optical	Single Mode	Single Mode
			Optical	Optical
Clock Recovery Phase Locked Loop Ba	ndwidth			
Internal Path Triggering		50 to 70 kHz		80 kHz
External Output		4 to 5 MHz		9 MHz
Data Rates (Mb/s)	155, 622, 1063, 1250, 2125, 2488, 2500	155, 622, 1063, 1250, 2125, 2488, 2500	155, 622, 1250, 2488, 2500	155, 622, 2488, 9953
Tracking/Acquisition Range		±0.1%		155, 622, 2488, ±0.1%; 9953 ±0.03%
Internal Splitter	50/50	50/50	10/90	10/90
Output Jitter		<0.0125 UI RMS		155, 622, 2488 0.02 UI RMS 9953 0.03 UI RMS
Input Power for Clock Recovery	-10 dBm to +3 dBm	750 to 860 nm,	-20 dBm to +3 dBm	-12 dBm to +3 dBm
		-10 to +3 dBm		(155, 622, 2488 Mb/s)
		1000 to 1600 nm,		-8 dBm to +3 dBm
		-13 to +3 dBm		(9953 Mb/s)
Input/Output Connectors	APC 3.5 mm, 50 ohm	FC/PC, 62.5/125 µm	FC/PC, 9 /125 µm	FC/PC 9/125 µm
		multimode	single mode	single mode
Auxiliary Recovered Clock and Regenerated Data Outputs		Type N with SMA adapters		
Input Return Loss	dc–1250 MHz, 20 dB 1250–2500 MHz, 15 dB	20 dB	28 dB	28 dB
Input Insertion Loss	dc–1250 MHz, 7 dB 1250–2500 MHz, 15 dB	5 dB Maximum	1.5 dB	Maximum



86109B 40Gb/s Optical Receiver Module Specifications

Historically, the 3 dB channel bandwidth has been the primary specification used to describe the ability of an oscilloscope to accurately display a high-speed waveform. As today's communication signals often have significant frequency content well beyond an oscilloscopes 3 dB bandwidth, it now becomes important to consider the oscilloscope response beyond the nominal 3 dB rolloff. If the response rolls off too fast or has an erratic phase response, the displayed waveform may exhibit significant distortion even if the 3 dB bandwidth is extremely high. Smooth phase response is the key to good pulse fidelity.

Rather than building the Agilent 86109B to have the highest 3 dB bandwidth, the frequency response has instead been carefully designed to achieve both a very fast channel with a FWHM (full-width-half-maximum) impulse response of approximately 12 ps with pulse aberrations typically less than 10%. Increasing the bandwidth beyond 40 GHz for an improved specification is possible, but within this system, the FWHM speed performance does not improve while the pulse aberrations degrade significantly.

Optical Channel Frequency Response ¹	
(Characteristic)	
Best Signal Integrity Mode	30 GHz (–2.5 dB)
	40 GHz (-3.5 dB)
	50 GHz (-4.5 dB)
Best Noise Performance Mode	26 GHz (3.0dB)
Impulse Risetime	8.5 ps
(10%to 90% level measured from impulse response ²)	
Impulse Pulse Width	12.0 ps
(FWHM measured from impulse response ²)	
Pulse Aberrations (pk-pk distortion)	<10 % pk-pk
Polarization Dependence	<0.5 dB
Wavelength Range	1000 to 1600 nm
Calibrated Wavelengths	1310 nm and 1550 nm
Optical Conversion	
1550 nm	10 V/W
1310 nm	12 V/W
RMS Noise ³	
Characteristic	50 μW (best pulse integrity mode)
	15 μW (best noise performance mode)
Maximum	70 µW (best pulse integrity mode)
	30 µW (best noise performance mode)
Scale Factor	
Minimum	20 μW/division
Maximum	1.0 mW/division
dc Accuracy	$\pm 50 \ \mu\text{W} \pm 4\%$ of (reading- channel offset)
(single marker, referenced to average power monitor, \leq 500 μ W/division)	
dc Difference	±4% of delta
(two markers, referenced to average power monitor, ≤500 µW/division)	
dc Offset	-2 mW to +6 mW
(referenced two divisions from screen bottom)	
Average Power Monitor	
(specified over operating wavelength range)	-23 dBm to + 9 dBm
	(5 μW to 8 mW)

OPTICAL CHANNEL SPECIFICATIONS

Factory Calibrated Accuracy	$\pm 5\% \pm 100 \text{ nW} \pm \text{connector uncertainty,}$
	20°C to 30°C
User Calibrated Accuracy	$\pm 2\% \pm 100$ nW \pm power meter uncertainty \pm connector uncertainty,
	<5°C change
Maximum Input Power	
Maximum displayed peak ⁴	8 mW (+9 dBm)
Maximum non-destruct peak	50 mW (+17 dBm), or 0.25pJ per pulse
Maximum non-destruct average	10 mW (+10 dBm)
Fiber Input	9/125 µm, user selectable connector type
Input Return Loss	
(HMS-10 connector fully filled single mode fiber)	30 dB

86109B 40Gb/s Optical Receiver Module Specifications (continued)

ELECTRICAL CHANNEL SPECIFICATIONS

Electrical Channel Bandwidth	26 and 50 GHz
Transition Time	
(10% to 90% calculated from TR = 0.35/BW)	<14 ps, 26 GHz
(Characteristic)	7 ps, 50 GHz
RMS Noise	
Characteristic	0.25 mV, 26 GHz
	0.60 mV, 50 GHz
Maximum	0.50 mV, 26 GHz
	1 mV, 50 GHz
Scale Factor (full height is eight divisions)	
Minimum	1 mV/division
Maximum	100 mV/division
dc Accuracy	
(single marker)	
26 GHz	±0.4% of full scale
	±2 mV ±1.5% of (reading -channel offset)
50 GHz	±0.4% of full scale
	±2 mV ±2% of (reading -channel offset)
dc Difference	
(two markers)	
26 GHz	±0.8% of full scale, ±1.5% of delta
50 GHz	±0.8% of full scale, ±2% of delta
dc Offset Range	
(referenced from center screen)	±500 mV
Input Dynamic Range	
(relative to channel offset)	±400 mV
Maximum Input Power	16 dBm ±2 Vdc
Nominal Impedance	50 ohm
Reflections - (for 30 ps rise time)	5%
Electrical Input Connector	2.4 mm

Specified with 8 point moving average. The frequency step is 200 MHz.
Measured with optical pulses with 5 ps FWHM, 10Gb/s repetition rate, and 2 mW peak power.
Measured with modules set at 1310nm 0/E conversion (responsivity) mode.
Maximum non-destruct power is related to the fill factor (duty cycle) of the RZ waveform. The factory specification is defined with using a 20% filled 40GB/s pulse train (i.e. 5ps FWHM and 25ps period). This concept can also be specified as maximum non-destruct pulse energy. The factory specification is specified with 5ps FWHM optical pulses and maximum non-destruct power providing that the individual pulse shape is square.

Ordering Information

86100A Option 001 Option AX4 Option AXE Option UK6	Infiniium DCA Mainframe, Wide Bandwidth Digital Oscilloscope 12 GHz Trigger Bandwidth Rack Mount flange Kit Rack Mount Flange Kit with Handles Commercial Cal Certificate with Test Data	Warranty Option Option W30 Option W32 Option W50 Option W52
86101A	High Sensitivity, Multimode, 3 GHz, 850 nm Optical and 20 GHz Electrical Module	Optional Access 10086A 11667B
Option 201 Option 202	OC-3/STM-1 (155 Mb/s), OC-12/STM-4 (622 Mb/s) FC (1.063 Gb/s), GBEN (1.25 Gb/s)	11667C 11898A 11982A
86103A Ontion 201	High Sensitivity, Multimode, 3 GHz, 1310/1550 nm Optical and 20 GHz Electrical Module OC-3/STM-1 (155 Mb/s)_OC-12/STM-4 (622 Mb/s)	54006A 54008B 54701A
Option 202	FC (1.063 Gb/s), GBEN (1.25 Gb/s)	83430A 83433A
86105A Option 101 Option 102	Single Mode, 20 GHz, 1310/1550 nm Optical and 20 GHz Electrical Module OC-3/STM-1 (155 Mb/s) OC-12/STM-4 (622 Mb/s)	83434A 83440B/C/D 83446A 83480A-KI6
Option 102 Option 201	OC-48/STM-16 (2.488 Gb/s) OC-12/STM-4 (622 Mb/s), OC-48/STM-16 (2.488 Gb/s)	83480A-KI7 N1020A N1025A
Option 202	OC-48/STM-16 (2.488 Gb/s), OC-192/STM-64 (9.953 Gb/s)	Connector Optic Option 011
86106B Option 410	Single Mode, 28 GHz, 1310/1550 nm Optical with standard OC-192/STM-64 (9.953 Gb/s) filter OC-192/STM-64 (9.953 Gb/s), 10 Gigabit Ethernet (10.3125 Gb/s), OC-192/STM-64 FEC (10.664 Gb/s, 10.709 Gb/s)	Option 012 Option 013 Option 014 Option 017
86109A	Single Mode, 30 GHz, Optical and 40 GHz Electrical Module	Additional Conn 11900B 11901B
86112A 83484A 83491A	Dual Channel 20 GHz Electrical Module Dual Channel 50 GHz Electrical Module Electrical Clock Recovery Module 155 622 1063 1250 2125 2488 2500 Mb/s	54124-24101 5061-5311 1250-1158 1810-0118
83492A	Multimode Clock Recovery Module 155, 622, 1063, 1250, 2125, 2488, 2500 Mb/s	
83493A 83494A	Single Mode Clock Recovery Module 155, 622, 1250, 2488, 2500 Mb/s Single Mode Clock Recovery Module	
83494A Option 106	155, 622, 2488, 9953 Mb/s Single Mode Clock Recovery Module 155, 622, 2488, 2666, 10664 Mb/s	
54753A 54754A	Single-ended TDR Module Differential TDR Module	

Warranty Options (for all products)

otion W30	3 years of customer return repair service
otion W32	3 years of customer return calibration service
otion W50	5 years of customer return repair service
otion W52	5 years of customer return calibration service

sories

0086A	ECL Terminator
1667B	Power Splitter, DC to 26.5 GHz, APC-3.5 mm
1667C	Power Splitter, DC to 50 GHz, 2.4 mm
1898A	Plug-in Module Remote/Extender
1982A	High-Speed Lightwave Receiver
54006A	6 GHz Resistive Divider Probe Kit
54008B	24 ns Delay Line
54701A	2.5 GHz Active Probe
33430A	2.5 Gb/s Lightwave Transmitter (1550 nm)
33433A	10 Gb/s Lightwave Transmitter
33434A	10 Gb/s Lightwave Receiver
33440B/C/D	Optical-to-Electrical Converters (6/20/34 GHz)
33446A	Lightwave Clock and Data Receiver
3480A-KI6	Switch Matrix
3480A-KI7	RIMM Fixture
N1020A	6 GHz TDR Probe Kit (passive)
N1025A	1 GHz Active Differential Probe

ons for All Optical Modules

)ption 011	Diamond HMS-10 Connector Interface
)ption 012	FC/PC Connector Adapter
Option 013	DIN Connector Adapter
)ption 014	ST Connector Adapter
Option 017	SC Connector Adapter

nection Devices for Electrical Modules

11900B	2.4 mm (f-f) Adapter
11901B	2.4 mm (f) to 3.5 mm (f) Adapter
54124-24101	2.4 mm Termination
5061-5311	APC 3.5 mm (f-f) Adapter
1250-1158	SMA (f-f) Adapter
1810-0118	3.5 mm Termination

Agilent Technologies'

Test and Measurement Support, Services, and Assistance

Agilent Technologies aims to maximize the value you receive, while minimizing your risk and problems. We strive to ensure that you get the test and measurement capabilities you paid for and obtain the support you need. Our extensive support resources and services can help you choose the right Agilent products for your applications and apply them successfully. Every instrument and system we sell has a global warranty. Support is available for at least five years beyond the production life of the product. Two concepts underlie Agilent's overall support policy: "Our Promise" and "Your Advantage."

Our Promise

Our Promise means your Agilent test and measurement equipment will meet its advertised performance and functionality. When you are choosing new equipment, we will help you with product information, including realistic performance specifications and practical recommendations from experienced test engineers. When you use Agilent equipment, we can verify that it works properly, help with product operation, and provide basic measurement assistance for the use of specified capabilities, at no extra cost upon request. Many self-help tools are available.

Your Advantage

Your Advantage means that Agilent offers a wide range of additional expert test and measurement services, which you can purchase according to your unique technical and business needs. Solve problems efficiently and gain a competitive edge by contracting with us for calibration, extra-cost upgrades, out-of-warranty repairs, and on-site education and training, as well as design, system integration, project management, and other professional engineering services. Experienced Agilent engineers and technicians worldwide can help you maximize your productivity, optimize the return on investment of your Agilent instruments and systems, and obtain dependable measurement accuracy for the life of those products.

By internet, phone, or fax, get assistance with all your test & measurement needs.

Online assistance: www.agilent.com/comms/lightwave

Phone or Fax United States:

(tel) 1 800 452 4844

Canada:

(tel) 1 877 894 4414 (fax) (905) 282 6495

China:

(tel) 800-810-0189 (fax) 1-0800-650-0121

Europe:

(tel) (31 20) 547 2323 (fax) (31 20) 547 2390

Japan:

(tel) (81) 426 56 7832 (fax) (81) 426 56 7840

Korea:

(tel) (82-2) 2004-5004 (fax)(82-2) 2004-5115

Latin America:

(tel) (305) 269 7500 (fax) (305) 269 7599

Taiwan:

(tel) 080-004-7866 (fax) (886-2) 2545-6723

Other Asia Pacific Countries:

(tel) (65) 375-8100 (fax) (65) 836-0252 Email: tm_asia@agilent.com

Product specifications and descriptions in this document subject to change without notice.

© 2000, 2001 Agilent Technologies Printed in USA June 29, 2001 5968-8546E

